

Framework for synchrophasor measurements data processing and the case studies of the low-frequency oscillations

A. Popov¹², K. Butin¹², D. Dubinin³, A. Rodionov¹


¹Engineering center “Energoservice”, Russia

²Northern (Arctic) Federal University, Russia

³System Operator of the United Power System, Russia



WAMS development in Russia




Low-frequency oscillations

- The experience shows that LFO occur more than **10 times a day** in the power system of Russia
- **Continuous online monitoring** of LFO and their **source detecting** in the dispatch center is required
- Challenges:
 - **low observability** of the power system
 - the source can be located in **neighboring countries**

Review 2015 – 2020

- **Focus of attention:** physics of oscillatory processes in big systems, detecting and identifying the low-frequency modes, developing new methods for locating the source of oscillations, real-time processing the large amounts of data, computational infrastructure.
- **Sequence of common subtasks:** data preprocessing, mode detection and selection, calculation the parameters of modes, source detection.



Set of solutions



$$N = \begin{matrix} n & \times & n & \times & n & \times & n \\ 1 & & 2 & & 3 & & 4 \end{matrix}$$

- Methods
- Parameters
- Implementations


Plan




- worker is activity
- plan may be worker

```
{  
  "class" : "WorkNode" ,  
  "id" : "freq" ,  
  "inputs" : [ "get_mode" ] ,  
  
  "work" : {  
    "descr" : "Get frequency of mode" ,  
    "worker" : {  
      "class" : "modulation.lqFreq" ,  
      "params" : {...}  
    }  
  }  
},  
  
"result" : {  
  "indep" : "Time" ,  
  "dep" : "Frequency [Hz]"  
}  
}
```

Varying the worker: get mode




FIR-filter (401 taps)




IIR-filter (Butterworth, 3 order, 14 taps)

Varying the worker: get mode



FIR-filter (301 taps)




IIR-filter (Butterworth, 3 order, 14 taps)

Dsplab

- Field of application: Development of the DSP routines that require a flexible configuration of different stages of calculations on the user level; **investigation of variety of methods** solving the same DSP task.
- User can define the **plan of works** and then set the workers. The replacement of the worker does not destroy the workflow.
- Types of nodes: **Work**, **Map (Loop)**, **Select** and **Pack**
- Licence: **LGPLv3**
- Programming language: **Python 3**

github.com/aleneus/dsplab

Parallel implementation




- There are different strategies for **splitting data** for parallel processing
- But the **functional nature of the plan** itself provides the automatic parallelism
- Suitable software development technologies: **“lightweight” threads, channels**


Real LFO cases

#	Date	Region	Number of data sources	Dataset	Record duration (min)	Mode (Hz)	Amplitude (P, MW), max	Duration of oscillations (min)
1	29.05.2018	North-central	83	f	5	0.5 - 0.7	-	1
2	07.03.2019	West	5	f, P, Q, U	4	0.7	12	3
3	02.05.2020	Central	114	P	2	0.13, 0.3	12	2
4	04.05.2020	Central	114	P	3	0.31	18	2
5	04.05.2020	Central	114	P	2	0.25 - 0.3	20	1
6	16.06.2020	West	116	f, P, Q, U	4	0.25 - 0.3, 0.11	22	1
7	02.09.2020	South	47	f, P, Q, U, I	3	0.25	40	2
8	24.09.2020	South	67	P, Q, U	5	0.2 - 0.3	55	0,5
9	25.11.2020	Syberia	202	f, P, Q, U	15	0.35	30	10

Case #7








a) Amplitude power spectrum
Energy Flow method



b) Dissipation

P and Q contribution

$$DEF_{ij}(t) = \int \left(\Delta P_{ij} d\Theta_i + \Delta Q_{ij} \frac{dV_i}{V^*_i} \right)$$



Conclusion

- Detection the source of LFO is one of the **many stages** of processing the synchrophasor measurements data.
- Due to the **growing variety of methods** for solving individual subtasks, program tools, allowing us to **explore** combinations of methods and **apply** the most successful ones are in demand.
- An approach to the representation of the data processing in the form of a generalized scheme (**plan**) with the possibility of variation of the used stage implementations is proposed.
- In the context of a generalized processing scheme, the **DEF method** has been successfully applied to analyze several real LFO cases in the power system of Russia.

Thank you for your attention!

Kirill Butin k.butin@ens.ru

Alexandr Popov a.popov@ens.ru

Dmitry Dubinin dubinin@so-ups.ru

Andrey Rodionov a.rodionov@ens.ru

